

THREE PHASE XFMRS			
Size - kva	208 amps	240 amps	480 amps
3	8.3	7.2	3.6
6	16.7	14.4	7.2
9	25.0	21.7	10.8
15	41.6	36.1	18.0
30	83.3	72.2	36.1
45	124.9	108.3	54.1
75	208.2	180.4	90.2
112.5	312.3	270.6	135.3
150	416.4	360.9	180.4
225	624.6	541.3	270.6
300	832.7	721.7	360.9
500	1387.9	1202.8	601.4
750	2081.9	1804.3	902.1
1000	2775.8	2405.7	1202.8

SINGLE PHASE XFMRS			
Size - kva	120 amps	240 amps	480 amps
1	8.3	4.2	2.1
1.5	12.5	6.3	3.1
2	16.7	8.3	4.2
3	25.0	12.5	6.3
5	41.7	20.8	10.4
7.5	62.5	31.3	15.6
10	83.3	41.7	20.8
15	125.0	62.5	31.3
25	208.3	104.2	52.1
37.5	312.5	156.3	78.1
50	416.7	208.3	104.2
75	625.0	312.5	156.3
100	833.3	416.7	208.3
167	1391.7	695.8	347.9
250	2083.3	1041.7	520.8
333	2775.0	1387.5	693.8
500	4166.7	2083.3	1041.7